



Elettra Sincrotrone Trieste



Elettra
Sincrotrone
Trieste


ADC behaviours in Electron Beam Position Detectors (eBPM)



Introduction to a eBPM Elettra project



- ✓ Goal of the project is the development of the prototype of an innovative device for measuring beam position, for rings such as Elettra, Elettra2 and single-pass machines such as Fermi
- ✓ A measurement system consisting of a RF section, an FPGA-controlled ADC section able to detect the position of the beam with sub-sampling techniques and a section capable of performing high-level processing (position calculation, calibration, system communication control). Fully integrated in Accelerator Control Systems (Tango, Epics) and compatible with the "environmental" constraints required by these devices.
- ✓ Spatial resolution less than 1μ @100Hz
- ✓ Long term stability (24hrs) **and** beam current dependence (70% machine range) less than 4μ rms
- ✓ Communication through two Gigabit Ethernet connections: one dedicated to global feedback, driven by acquisition FPGA, with position data transmission > 20KHz
- ✓ **MODULAR SYSTEM:** Stand alone FrontEnd, digitizer and timing system.

eBPM: Block Diagram



eBPM: RF Front End



- RF Front End can be placed in machine tunnel to:
Compensate also the long run cables
Have better s/n ratio






Elettra
Sincrotrone
Trieste

RF Front End in tunnel test bench







Real beam 24hrs data acquisition @Elettra



“Wobbled” cables during acquisition @ Diamond Light Source


Courtesy of G. Rehm




ADC System

Currently @Elettra we are developing a new uTCA board (project name ADx)



ADx simplified Block diagram V3.1



FMC Module : 4X ADC, 16-Bit, 210 MSPS




ADC Measurement system diagram



Data Acquisition system software

The acquisition software acquires 2.6Msamples of raw data from the ADC @150Ms/s. Then it computes an FFT on these data and it finds the peaks for the two tones. The amplitudes of these peaks are used to calculate the positions respectively for the carrier (@499.654 MHz) and for the pilot tone (@503.123 MHz)





ADC tests: LTC 2209 ADC characteristics

CONVERTER CHARACTERISTICS The ● denotes the specifications which apply over the full operating temperature range, otherwise specifications are at $T_A = 25^\circ\text{C}$. (Note 4)

PARAMETER	CONDITIONS		MIN	TYP	MAX	UNITS
Integral Linearity Error	Differential Analog Input (Note 5)	●		± 1.5	± 5.5	LSB
Differential Linearity Error	Differential Analog Input	●		± 0.3	± 1	LSB
Offset Error	(Note 6)	●		± 2	± 10	mV
Offset Drift				± 10		$\mu\text{V}/^\circ\text{C}$
Gain Error	External Reference	●		± 0.2	± 2	%FS
Full-Scale Drift	Internal Reference External Reference			± 30 ± 15		ppm/ $^\circ\text{C}$ ppm/ $^\circ\text{C}$
Transition Noise	External Reference			3		LSB _{RMS}

2209fb

Note 5: Integral nonlinearity is defined as the deviation of a code from a “best fit straight line” to the transfer curve. The deviation is measured from the center of the quantization band.

ADC tests: position algorithm considerations

ADC offset definition: with 0 (no) input signal the ADCs have to read 0 (zero) code
In practice this never happens!.

What does it means? What are the effects?


Level (gain)	ADC A	ADC B	ADC C	ADC D		zero A	zero B	zero C	zero D		X µm	Y µm
1	4000	4000	4000	4000		8	6	2	5		-6,26	-8,76
2	8000	8000	8000	8000		8	6	2	5		-3,13	-4,38
3	12000	12000	12000	12000		8	6	2	5		-2,08	-2,92
4	16000	16000	16000	16000		8	6	2	5		-1,56	-2,19
5	20000	20000	20000	20000		8	6	2	5		-1,25	-1,75
6	24000	24000	24000	24000		8	6	2	5		-1,04	-1,46
7	28000	28000	28000	28000		8	6	2	5		-0,89	-1,25

$$X = 20000 * \frac{((adcA - zeroA) + (adcD - zeroD)) - ((adcB - zeroB) + (adcC - zeroC))}{(adcA - zeroA) + (adcB - zeroB) + (adcC - zeroC) + (adcD - zeroD)}$$

$$Y = 20000 * \frac{((adcA - zeroA) + (adcB - zeroB)) - ((adcC - zeroC) + (adcD - zeroD))}{(adcA - zeroA) + (adcC - zeroC) + (adcB - zeroB) + (adcD - zeroD)}$$

With these data is possible to evaluate the weight of a **little** offset (compared to the whole signal) as specified as the typical integral non-linearity value in ADC datasheet.

The sum over difference algorithm is sensitive to the ADC offset.



ADC tests: Zero Offset measure


Zero Offset is the effective ADC value for 0 (no) signal input.

The way to measure is to use a “best fit straight line” to the transfer curve.

Due to a measure method (using dB attenuators) a logarithmic scales have been used.

That means that no zero intercept point between axes exists.


Then a max -80dB point was chosen.



ADC tests: Zero Offset measure


Pilot (503.123) From +10 to 0 dBm

All of the acquired points are a mean of 20 points normalized at +10



ADC tests: Zero Offset measure


Carrier (499.654 MHz) From -20 to -30 dBm --- Same mechanical steps as +10 to 0
All of the acquired points are a mean of 20 points normalized at -20



ADC tests: Zero Offset measure

Pilot (503.123 MHz) From **-20 to -30 dBm --- Same mechanical steps as +10 to 0**

All of the acquired points are a mean of 20 points normalized at -20





ADC tests: Zero Offset and integral nonlinearity

The line fitting shows that the ADC integral linearity is **affected by the input level**.
The ADC integral linearity affects the ADC zero offset.
Then the position calculated is affected by ADC input level.

0 to -10 dBm, step-2, mean20												
meanAc	meanBc	meanCc	meanDc	meanAp	meanBp	meanCp	meanDp	Xc	Yc	Xp	Yp	
0,1894	0,1904	0,1898	0,1893	0,2049	0,2060	0,2054	0,2048	-38,14	18,85	-37,92	18,64	
0,1508	0,1516	0,1511	0,1507	0,1630	0,1638	0,1633	0,1629	-38,27	18,63	-37,80	18,80	
0,1209	0,1216	0,1212	0,1208	0,1307	0,1314	0,1310	0,1306	-38,53	18,79	-37,93	18,89	
0,0954	0,0960	0,0956	0,0954	0,1031	0,1036	0,1033	0,1030	-38,56	18,50	-37,44	19,18	
0,0764	0,0768	0,0766	0,0764	0,0828	0,0832	0,0829	0,0827	-38,61	18,14	-36,86	19,63	
0,0607	0,0610	0,0608	0,0607	0,0656	0,0660	0,0658	0,0656	-38,88	18,04	-36,88	19,92	
RMS:								0,24	0,30	0,46	0,46	

A possible solution is to use (also) the pilot tone amplitude to keep the ADC inputs levels constant when the carrier signal (from machine) is varying.

SAME LEVEL ($\pm 27K$ pk-pk), 0 to -10 dBm carrier, step -2 ,mean 20, pil step3												
meanAc	meanBc	meanCc	meanDc	meanAp	meanBp	meanCp	meanDp	Xc	Yc	Xp	Yp	
0,1895	0,1905	0,1899	0,1894	0,2054	0,2064	0,2058	0,2052	-38,10	18,85	-37,92	18,65	
0,1505	0,1513	0,1508	0,1504	0,2312	0,2324	0,2317	0,2311	-38,09	18,84	-37,67	18,82	
0,1202	0,1208	0,1204	0,1201	0,2607	0,2620	0,2612	0,2605	-37,99	18,84	-37,70	18,76	
0,0934	0,0939	0,0936	0,0934	0,2897	0,2912	0,2903	0,2895	-38,03	18,65	-37,77	18,70	
0,0747	0,0751	0,0749	0,0747	0,3285	0,3303	0,3292	0,3283	-38,01	18,78	-37,80	18,61	
0,0590	0,0593	0,0592	0,0590	0,3672	0,3692	0,3680	0,3670	-38,10	19,23	-37,84	18,61	
RMS:								0,04	0,18	0,08	0,08	



ADC tests: Conclusions

- Direct RF undersampling with high speed ADC is actually the best cost/benefits solution to acquire the signals for a BPM system.
- But the high speed ADC like LTC 2209 have some intrinsic behaviours that have to be considered. These behaviours may influence the beam current dependence.
- Some techniques and some strategies in Automatic Gain Control and/or in the pilot tone compensation are required to reduce at the minimum possible the effects due to integral non-linearity of the ADCs.
- The “modular approach” for a BPM system can help to better understand the behaviours of each part.



Elettra
Sincrotrone
Trieste

Thank you!




Elettra
Sincrotrone
Trieste



www.elettra.eu



Elettra
Sincrotrone
Trieste









Elettra
Synchrotron

Single Tone -6 to -36





Carrier position: 499 MHz from -6 dBm to -36 dBm









Elettra
Sincrotrone
Trieste

Single Tone -6 to -36







Dual Tone Constant Power -6 to -36

Carrier position: 499 MHz from -2 dBm to -30 dBm



Dual Tone Constant Power -6 to -36

Pilot position: 503 MHz from -30 dBm to -2 dBm



Dual Tone Constant Power -6 to -36

Compensated position of carrier

